

NONEL[®] EZ DET[®] 1.4B

Technical Information



Application Recommendations (continued)

- **ALWAYS** protect the plastic EZ Connector block and all shock tube leads from impact or damage during the loading and stemming operations. Use care when placing blasting mats and cover material on top of the blasting circuit. The EZ Connector block contains a detonator and is subject to detonation caused by abuse such as impact. Shock tube which has been cut, ruptured or damaged may cause misfires.
- **ALWAYS** be sure that the shock tube(s) are securely inserted, one at a time, into the EZ Connector block. The head of the EZ Connector block should rise to accept the shock tube and return to a closed position with an audible click.
- **ALWAYS** ensure that individual shock tubes remain aligned side by side in the connector channel and do not cross one over the another on insertion.
- **NEVER** use NONEL EZ DET units with detonating cord. The low strength surface detonator will not initiate detonating cord and may cause misfires.
- **NEVER** attempt to disassemble the delay detonator from the plastic EZ Connector block or use the detonator without the connector.
- **NEVER** place more than 6 shock tube leads into the plastic EZ Connector block. Misfires may result.
- **NEVER** pull, stretch, kink or put tension on shock tube such that the tube could break.
- **NEVER** splice NONEL EZ DET shock tube together to extend between holes.
- **NEVER** connect NONEL EZ DET units together until all holes have been primed, loaded and stemmed and the blast site has been cleared.

Transportation, Storage and Handling

- NONEL EZ DET must be transported, stored, handled and used in conformity with all federal, state, provincial and local laws and regulations.
- For maximum shelf life (3 years), NONEL EZ DET must be stored in a cool, dry, well ventilated magazine. Explosive inventory should be rotated. Avoid using new materials before the old. For recommended good practices in transporting, storing, handling and using this product, see the booklet "Prevention of Accidents in the Use of Explosive Materials" packed inside each case and the Safety Library Publications of the Institute of Makers of Explosives

Packaging

Length		Case Type	Quantity / Case	
m	ft		case	subpack
3.5	12	D	180	90
4.5	16	D	120	60
7	24	D	120	60
9	30	D	80	40
12	40	D	60	30
15	50	D	60	30
18	60	D	50	25
24	80	DC	50	--
30	100	DC	40	--
37	120	DC	30	--

- Length rounded to nearest one-half meter.
- Case weight varies by length & delay; see case label for exact weight.

Note: This product is also available with a High Strength cap. For more information, please contact your local Dyno Nobel sales representative.

Case Dimensions

Detpak Case (DC)	48 x 45 x 26 cm	18¾ x 17¾ x 10¼ in
Detpak (D)		
subpack	44 x 22 x 25 cm	17 ½ x 8 ¾ x 10 in
strapped case	44 x 45 x 25 cm	17 ½ x 17 ⅝ x 10 in

Product Disclaimer Dyno Nobel Inc. and its subsidiaries disclaim any warranties with respect to this product, the safety or suitability thereof, or the results to be obtained, whether express or implied, INCLUDING WITHOUT LIMITATION, ANY IMPLIED WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE AND/OR OTHER WARRANTY. Buyers and users assume all risk, responsibility and liability whatsoever from any and all injuries (including death), losses, or damages to persons or property arising from the use of this product. Under no circumstances shall Dyno Nobel Inc. or any of its subsidiaries be liable for special, consequential or incidental damages or for anticipated loss of profits.

Dyno Nobel Inc.

2795 East Cottonwood Parkway, Suite 500, Salt Lake City, Utah 84121 USA
Phone 800-732-7534 Fax 801-328-6452 Web www.dynonobel.com

DYNO[®]
Dyno Nobel

Groundbreaking Performance[™]